

Inverter Modified Sine Wave POWERTECH 300W 12V

DC Input voltage	DC10-15V
Output power	300W
Output power surge	1000W
Low battery alarm	10.5 ± 0.5V
Low battery shut down	10 ± 0.5V
High battery shut down	15.5 ± 0.5V
Short-circuit protection	YES
No load current	< 0.3A
Alarm and Thermal shut down	60°C ± 5°C
Alligator clip FUSE	35A
Cigarette plug FUSE	15A
Dimensions(LxWxH)	190x91x58 mm
Net Weight	1.1Kgs

Connect the red cable from the "+" terminal (red terminal) of the battery to the + binding post (red connection) of the inverter and the black cable from the "-" terminal (black terminal) of the battery to the "-" binding post (black connection) of the inverter. (for 150w - cigarette plug only)

Be sure to tight the screws in order to avoid loose connection.

Cable length ≤ 2m.



1. DESCRIPTION

